



**The Ground Switcher
with Remote Control**



Remotely Control your Streetlights

The Ground Switcher is ideal for applications where you need to remotely turn off your streetlights. This device goes between the streetlight and the photocontrol giving you the ability to shut down the luminaire indefinitely. The streetlight can be activated and deactivated through a remote-control device and has a distance of up to 100' line of sight. The Ground Switcher twists and locks into the ANSI C136 receptacle on the top of the luminaire and has the ability to accept any photocontrol device, either 3-pin or 7-pin, on its top side.

Specifications

Model Number	RC8801	7-Pin Pass Through
Voltage Rating	120VAC, 60Hz Only	<i>Note: higher voltage may be available</i>
Current Rating	10 Amps	Continuous AC
Operating Temperature	-40°C to +70°C	-40°F to +158°F
Wireless Remote	Simple On/Off Remote	Operates up to 100'
Wireless Frequency	TBD	FCCID: TBD
Housing	Polypropylene Black	UV Stabilized, Impact Resistant
Base	Polycarbonate	UL94HB Flame Class Rating
Gasket	Neoprene	ASTM D 1056

Note: Photocontrols sold separately

The information in this document is provided for informational use only and is subject to change without notice.